

ISSUED DEC. 21 2018		FRAME ALLOCATION			MODEL AFHH	
REVISED JUN. 28. 2019		3-PHASE HIGH EFFICIENCY INDUCTION MOTORS LOW VOLTAGE SQUIRREL CAGE			460V 60Hz	
OUTPUT HP	2P FRAME NO.	4P FRAME NO.	6P FRAME NO.	8P FRAME NO.		
200	—	—	—	5009B		
250	—	—	—	5009B		
300	—	—	5009B	5009B		
350	5009A	5009B	5009B	5009B		
400	5009A	5009B	5011B	5011B		
450	5009A	5009B	5011B	5011B		
500	5011A	5011B	5011B	5810B※		
600	5011A	5011B	5011B※	5810B※		
700	5011A※	5011B※	5810B※	5810B※		
800	5810A※	5810B※	5810B※	6808B※		
900	—	5810B※*	5810B※*	6808B※*		
1000	—	5810B※*	—	—		
<p>NOTE: 1. WITH "※" : COPPER ROTOR WITHOUT "※" : ALUMINUM ROTOR</p> <p>2. MULTIPLE MOUNTING DIMENSIONS FOR EACH FRAME NO. FRAME 5009: MOUNTING HOLE WITH 5009 &amp; 5007 FRAME 5011: MOUNTING HOLE WITH 5011, 5010 &amp; 5009</p> <p>3. WITH " * " : NO CSA CERTIFICATION (4~8P 900HP AND 4P 1000HP).</p>						
APPD.	B.LIN	JUN. 28. 2019	TECO Electric & Machinery Co., Ltd.			DWG NO.
CHKD.	H.Y.WANG	JUN. 28. 2019				3A057M285E
DWN.	H.F.KUO	JUN. 28. 2019				REV.02